

InfoStroyer™ 201

CUTTING EDGE DATA DESTRUCTION

DESTROYS

CD's • DVD's
Paper Documents
Punched Key Tape
Magnetic Tape
Films • Negatives • Microfilm
ID Badges • Smart Cards
Plastic Credit Cards



BENEFITS

Restricted Space Configurations
Surface Vessels / Submarines
Aircraft / Deployable
Destroys all forms of media
Self Healing Cutting System
Auto Jam Clearing

DocuStroyer™ technology covered under U.S. patent numbers 6,938,844 7,090,214 7,090,156 7,100,852. Other U.S. and foreign patents pending

InfoStroyer™ 201 has been evaluated by the NSA and meets the requirements of NSA/CSS 02-02, High Security Disintegrators and NSA/CSS 04-02, Optical Media Destruction Devices

Specifications

Throat Width

9"

Power

115v/1/60Hz/20 amps (standard)

50-60Hz switch selectable (optional)

Weight

71 - 75 lbs.

Dimensions (H x W x D)

201-O - 14" x 20" x 16", 201-D - 15.5" x 20" x 16"

Cart – (optional)

38" L x 19" W x 33" H (assembled 34 pounds)

Cutting System, Zero Clearance

Single moving part, **SELF HEALING**

Jam Clearing

Automatic or Manual (operator command)

Residue Collection

High volume external vacuum 6-16 Gal. (optional)

(internal vacuum system for emergency use only)

Residue Dimension

DUST-like particles, smallest available globally

Throughput

Paper Capacity

Up to 20 sheets single pass (8.5 x 11, 20lb)

CD's, DVD's

Up to 720 per hour

Punched Key Tape

Up to 20 pieces single pass or bunch feed

Floppy Disc (metallic hub removed)

720 per hour (also destroys plastic floppy case)



Proudly Made In The USA



Applied Magnetics Lab., Inc. • 1404 Bare Hills Rd. • Baltimore, MD 21209
ph: 800.754.1619 • fx: 410.583.8315 • www.infostroyer.com • sales@infostroyer.com

InfoStroyer™ 201 Configurations



201-O Bundle

(Shown with model 201-O, cart and collection system)



201-O Bundle with ATA Transport Case

(ATA case available with models 201-O and the 201-D)



201-D

(Configured for on-campus mobile requirement)



201-O

(Shown with 1 gal. bag for low volume or emergency use)



201-Transit - Smallest Deployment Configuration

(Shown with models 201-O and the 201-D)



Startup Kit

Ships with each unit and includes the following:
Operator & Service Manuals
InfoStroyer™ Bags (6) • Emergency Bag Adapter
Bed Blade • Drive Belt • Lubricant
Applicator Brush • (3) T-Handle Hex Key Wrenches



Applied Magnetics Lab., Inc. • 1404 Bare Hills Rd. • Baltimore, MD 21209
ph: 800.754.1619 • fx: 410.583.8315 • www.infostroyer.com • sales@infostroyer.com